



Product Info

Aerials | Dishes | Receivers | Headends | Multi switches | Amplifiers | Outlets | Home accessories | Fibre cabinets | Enclosures

Extension unit CSE 3301

If you have a CSE 3300 headend system where all slots for modules are in use, and there is a need for extra/new channels, you can add one cassette (2 channels) to the existing headend system with the new CSE 3301 unit.

- The extension unit is 1 unit high and fits into a 19" rack
- Slot for 1 cassette (up to 2 channels)
- Suitable for all analogue, digital TV and radio cassettes with integrated microcontroller
- Programming via control unit BE REMOTE L (not available/included in the delivery)



Type	CSE 3301 Extension
Art. No.	325103
No. of slots for cassettes	1
Delivery status	unloaded
Fit for adjacent channels	yes
Input/output impedance / Programming	75 Ω/via external control unit BE REMOTE or BE-REMOTE PROFF.
S/N weighted	55 dB
Input data	
Input frequency range	47 – 862 MHz, 950 – 2150 MHz
Input distributor	-
Power feed for LNC	-
Output data	
RF output level/ RF level adjusting	max. 80 dBμV/-
Output frequency range dependent upon cassettes	47 – 862 MHz
Power supply	
Mains voltage/Frequency 50/60 Hz	12 V DC via wall power supply unit
Power consumption max.	approx. 20 W
Weight (fully loaded)	approx. 3.3 kg
Dimensions (W x H x D)	approx. 48.2 (19") x 4.3 (1 HU) x 20.5 cm

TRIAX A/S

Bjørnkærvej 3 • DK-8783 Hornsyld
+45 76 82 22 00 • +45 75 68 79 66
mail: triax@triax.dk • www.triax.com



TRIAX - your ultimate connection